

MC 521 YELLOW LABEL SETUP FOR SINGLE FULL POWER

Power **ON**

Turn Mode selector switch to **CLOSED** or **OFF**

Remember when releasing enter you only have 2 seconds to make a change

A) Hold enter and press down to #99

Release enter, press down one time to #00

B) Hold enter and press down to #96

Release enter, press up one time to #01

You will then see "A0" on display

C) Hold enter and press up to #00

Release enter, press up to until you see #05

You will then see "AO" on display

D) Hold enter and press up to #01 (motor 01)

Release enter, go to "00" for right hand or "01" for left hand

You will then see "A0" on display

E) Hold enter and press up to #03

Release enter, press **UP** one time

You will see "20" briefly, then "A1" on display

F) Hold enter and press up to #11

As long as you don't have sentrex, release enter and change it to #00

You will see "A1" on display

- G) With the door in the **fully closed position**, you will now flip your mode switch to <u>HOLD OPEN</u>. **AS SOON AS THE DOOR BEGINS TO MOVE, FLIP THE MODE SWITCH BACK TO CLOSED/OFF**. The door will now go thru a "learn" process. This consists of the door opening and closing several times until you see "A2" on the display. Once "A2" is present you will:
- H) Hold enter and press down to #99

Release enter, press up one time to "01"

It will then read "20" briefly, then go to "00"

At this point you may put your switch to **AUTOMATIC** and run your door.